Reyrolle Protection Devices

# 7PG17 - XR

Intertripping, Interposing, Supervision and Special Purpose Relays.

**Answers for energy** 



## 7PG17-XR309

Intertripping, Interposing, Supervision and Special Purpose Relays.

### XR309 - Site Test Method

During service this relay is connected to a 3 wire voltage supply. If all or none of the elements are operating there is no output from the relay contacts. If one element drops off then there is an output from the relay contacts.

To test the pick up level of each element, voltage is applied to the terminals shown below in table 1 and increased until the relay operates. The pick up is not greater than 40v ac and the drop off is not less than 25v ac.

NOTE: There is no operation of the output contacts during this test the operation of the element can only be observed visually. If necessary the relay can be removed from its box and connections made to the rear connecting block.

Voltage between Terminals	Elements Operated	
23-25	А	
25-27	В	
23-27	C	

#### Table 1

To prove the relay contacts operate single phase voltage is applied to two of three elements via the connections shown in table 2. In the test the contacts 1& 3 can be monitored.

Live	Neutral	Element Operated
25,27	23	A & C
23,27	25	A & B
23,25	27	B & C

### Table 2

This relay is an instantaneous operating element; for time delayed operation an external time delayed relay is required.



Published by and copyright © 2010: Siemens AG Energy Sector Freyeslebenstrasse 1 91058 Erlangen, Germany

Siemens Protection Devices Limited P.O. Box 8 North Farm Road Hebburn Tyne & Wear NE31 1TZ United Kingdom

Phone: +44 (0)191 401 7901 Fax: +44 (0)191 401 5575 www.siemens.com/energy

For more information, please contact our

Customer Support Center.
Phone: +49 180/524 70 00

Fax: +49 180/524 24 71(Charges depending on provider)

E-mail: support.energy@siemens.com

Power Distribution Division Order No. C53000-G7076-C63-1 Printed in Fürth

Printed on elementary chlorine-free bleached paper.

All rights reserved.

Trademarks mentioned in this document are the property of Siemens AG, its affiliates, or their respective owners.

Subject to change without prior notice.

The information in this document contains general descriptions of the technical options available, which may not apply in all cases. The required technical options should therefore be specified in the contract.

