

# 3RV Motor Starter Protectors/Circuit Breakers up to 100 A

## Accessories

### Rotary operating mechanisms

#### Technical specifications

##### Remote motorized operating mechanisms

Type		3RV19 36, 3RV19 46
<b>Max. power consumption</b>	W	48
• At $U_s = 24$ V DC		
• At $U_s = 230$ V AC	VA	170
<b>Operating range</b>		$0.85 \dots 1.1 \times U_s$
<b>Minimum command duration</b> at $U_s$	s	0.1
<b>Max. command duration</b>		Unlimited (uninterrupted operation)
<b>Max. total break time</b> , remote-controlled	s	2
<b>Ready to reclose</b> after approx.	s	2.5
<b>Switching frequency</b>	1/h	25
<b>Internal back-up fuse</b>		
• 230 V AC	A	0.8
• 24 V DC	A	1.6
<b>Connection type of control cables</b>		Plug-in connectors with screw terminals
<b>Shock resistance acc. to IEC 60068-2-27</b>	g/ms	25/11 (square and sine pulse)